

Akai APC40 MKII Layout V3.4

Midi Template File name: Advanced APC40 Template (version 3.4).BeyondMidiMap

Midi templates can be found inside the subdirectory "MIDI" of "BEYOND". (example C:\BEYOND\MIDI*)

PANGOLIN LASER SYSTEMS

APC40 MKII

APC40MKII
 Template Version 1.9 for
BEYOND 2.1 b790 and up
 After BEYOND is finished initializing
 the midi controller, move all sliders to
 your preferred start position.
 The ScanRate is limited to values set
 in the 'projector settings' scan rate tab.

Toggle Cues
 Off - Empty Cue
 Slow Blinking White - Empty Cue Focused
 Blue/Yellow - Cue with Content
 Blinking Blue/Yellow - Focused Cue with Content
 Blinking Red - Cue Playing
 Fast Blinking Red - Focused Cue Playing

Toggle Zone Mute zone 1 - 8
 Toggle Zone Output zone 1 - 8
 QuickFX row 1 & [3] fx 1 - 16
 QuickFX row 2 & [4] fx 1 - 16

MASTER BRIGHTNESS
 QuickFX 1 Action
 QuickFX 2 Action
 QuickFX 3 Action
 Zoom
 Visible Points
 Scan Rate
 Animation Speed
 Color Slider

Commands between [] are only available while holding down the Shift button (button 30).

1 - Master Pause	11 - Blackout	21 - Reset Angle	31 - Capture QuickCapture [Store in focused Cue]	I - Friction [Mass]
2 - Toggle Physics	12 - Previous Transition	22 - Live and QuickFX to Master	A - Size X	J - BPM Shift
3 - Invert Play Direction	13 - Resync [Toggle VLJ]	23 - Live and QuickFX to Cue	B - Size Y	K - Position Y
4 - Swap playing Cue [Previous Cue]	14 - Tap Beat [Set BMP to 120]	24 - Live and QuickFX to Zone	C - Fog/Haze (DMX address 1)	L - Rotation X
5 - Toggle Muted Zones by BPM	15 - Toggle lock XY Size	25 - Alpha Pulse (All Zones)	D - Red	M - Rotation Y
6 - Toggle Muted Zones Manually	16 - BPM Divided by 2 [by 4]	26 - Previous category [focus to left]	E - Green	N - Rotation Z
7 - Reset Zone and Mute Selection	17 - BPM Multiplied by 2 [by 4]	27 - Previous Page [focus one up]	F - Blue	O - Position X
8 - Next Transition	18 - Reset Position	28 - Next Page [focus one down]	G - Alpha	P - Angle X
9 - Enable Laser Output	19 - Stop rotation [Reset rotation]	29 - Next category [focus to right]	H - Transition Speed	Q - Angle Y
10 - Disable Laser Output	20 - Invert rotation	30 - Shift [activates Layer 2]		R - Angle Z

From: <http://wiki.pangolin.com/> - Complete Help Docs

Permanent link: <http://wiki.pangolin.com/doku.php?id=beyond:akaiapc40mkiilayout&rev=1568057271>

Last update: 2020/06/11 19:23

